

Line	DB 25 male (computer)	Centronics (printer)
Strobe	1 →	1
Data bit 0	2 →	2
Data bit 1	3 →	3
Data bit 2	4 →	4
Data bit 3	5 →	5
Data bit 4	6 →	6
Data bit 5	7 →	7
Data bit 6	8 →	8
Data bit 7	9 →	9
Acknowledge	10 ←	10
Busy	11 ←	11
Paper out	12 ←	12
Select	13 ←	13
Autofeed	14 →	14
Error	15 ←	32
Reset	16 →	31
Select	17 →	36
Signal ground	18 ↔	33
Signal ground	19 ↔	19 + 20
Signal ground	20 ↔	21 + 22
Signal ground	21 ↔	23 + 24
Signal ground	22 ↔	25 + 26
Signal ground	23 ↔	27
Signal ground	24 ↔	28 + 29
Signal ground	25 ↔	16 + 30
Shield	Cover ↔	Cover + 17

